



	N	NEUTRAL
	E	EARTH
	L	PERMANENT LIVE
	SL	SWITCHED LIVE

Non Maintained Operation: Connect to L, E, N only.

Maintained Operation: Connect to L,E,N and link L to SL.

For Switchable Maintained Operation: Connect to L,E, N and connect switch live to terminal marked SL

INSTRUCTIONS

- Remove lid and diffuser by unscrewing the 5 retaining screws.
- Unscrew the 2 retaining screws that hold the gear tray and twist off the key holes.
- Drill and plug holes in preparation for the luminaire.
- Apply anti-pick mastic to the outer rim.**
- Feed the mains cable through the entry hole in the base. Secure it with a suitable cable gland. Please ensure any cable entries and screw fixings have been adequately sealed if this luminaire is to be used in exterior applications.
- Once the unit is securely fixed, connect the electrical cable. Secure the gear tray into the housing by re-fitting the two screws. Fit the gasket seal if the luminaire is to be used outdoors and then re-fit the diffuser.
- After the installation of the luminaire restore/connect the mains supply. Check that the green LED indicator is operational, indicating that the battery is charging. All self-contained luminaries should be allowed to charge for at least 24 hours before carrying out a full emergency mode duration test. Isolate the power supply and check that the light remains illuminated for 3 hours. Restore the power supply.
- Apply anti-pic mastic from the outside to ensure that there are no gaps between the luminaire and wall/ceiling surface.

IMPORTANT WARNINGS

Do not install the luminaire in areas without sufficient air circulation. The manufacturer cannot be considered liable for any damage caused by inappropriate use of the luminaire other than its manufactured purpose.

Luminaries must be installed by a qualified registered electrician only. Any misuse of the luminaire when power is activated may cause the risk of an electric shock.

The manufacturer does not accept any responsibility of any issues resulting from the non-compliance of the recommendations included in this instruction document. These instructions are issued as a guide to assist the installer to satisfactory conclusion.

The manufacturer reserves the right to change the design of this product without prior notice.

WASTE DIRECTIVE

The European Directive 2002/96/EC on waste electrical and electronic equipment requires that electric and electronic devices must not be disposed of in the normal household waste. For correct disposal, please use authorized waste disposal facilities or return to the distributor at the date a new lighting fitting is purchased. Lamps, if disposed together with the lighting fitting, should not be broken up as they contain pollutants, which are harmful to the environment. Unauthorized disposal of the foregoing waste material is punishable by law.

